




































































































































































Feature Matrix for FortiSwitchOS 7.0.3

The following table lists the FortiSwitch features in Release 7.0.3 that are supported on each series of FortiSwitch models. All features are available in Release 7.0.3, unless otherwise stated. Features marked with ✓ are supported by FortiSwitch units in standalone mode; features marked with  are supported in both standalone and in FortiLink mode. Security Fabric features are available exclusively in FortiLink mode.

Feature	GUI Supported	112D-POE	FSR-124D	1xxE, 1xxF	4xxE	200 Series, 400 Series	500 Series	1024D, 1024E, 1048D, 1048E, T1024E	3032D, 3032E
Security Fabric (exclusively in FortiLink mode)									
Centralized configuration									
Centralized firmware management									
Automated detection and recommendations									
Syslog collection	—								
Device detection									
Network device detection	—	—		—					
Block intra-VLAN traffic (See Note 8.)									
Host quarantine									
Integrated FortiGate network access control (NAC) function									
NAC LAN segments	—	—		 (124F, 124F-POE, 124F-FPOE, 148F, 148F-POE, 148F-FPOE)					

Feature	GUI Supported	112D-POE	FSR-124D	1xxE, 1xxF	4xxE	200 Series, 400 Series	500 Series	1024D, 1024E, 1048D, 1048E, T1024E	3032D, 3032E
FortiGuard IoT identification									
Support of matching FortiClient EMS tags in NAC policies									
Dynamic port policies									
Management and Configuration									
CPLD software upgrade support for OS	—	—	—	—	—	—	—	1024D, 1048D	—
Firmware image rotation (dual-firmware image support)	—	✓	✓	148E, 148E-POE	✓	✓	✓	✓	✓
HTTP REST APIs for configuration and monitoring	—	✓	✓	✓	✓	✓	✓	✓	✓
Support for switch SNMP OID									
IP conflict detection and notification	✓	✓	✓	✓	✓	✓	✓	✓	✓
FortiSwitch Cloud configuration	✓	✓	✓	✓	✓	✓	✓	✓	✓
Auto topology	—								
Security and Visibility									
802.1x port mode									
802.1x MAC-based security mode									
User-based (802.1x) VLAN assignment									
802.1x enhancements, including MAB									
MAB reauthentication disabled	—	✓	✓	✓	✓	✓	✓	✓	✓
open-auth mode									
allow-mac-move	—	—	✓	—	—	✓	✓	1024D, 1048D	3032D

Feature	GUI Supported	112D-POE	FSR-124D	1xxE, 1xxF	4xxE	200 Series, 400 Series	500 Series	1024D, 1024E, 1048D, 1048E, T1024E	3032D, 3032E
FIPS 140-2 (Level 2) support	—	—	—	—	 (424E, 424E-FPOE, M426E-FPOE, 424E-Fiber, 448E, 448E-FPOE)	—	—	 (1024E, 1048E, T1024E)	 (3032E)
Layer 2									
Link aggregation group size (maximum number of ports) (See Note 2.)	✓	8	8	8	8	8	24/48	24/48	24/64
LAG min-max bundle	—								
IPv6 RA guard	—	—	—	—	✓	✓	✓	✓	✓
IGMP snooping	✓								
IGMP proxy	✓								
IGMP querier	—								
MLD snooping	—	—	—	—	—	—	✓	✓	✓
MLD proxy	—	—	—	—	—	—	✓	✓	✓
MLD querier	—	—	—	—	—	—	✓	✓	✓
LLDP transmit	—								
LLDP-MED	—								
LLDP-MED: ELIN support	✓								
Per-port max for learned MACs	—	—						—	—
MAC learning limit (See Note 4.)	—							—	—
Learning-limit violation log (See Note 4.)	✓							—	—
Learning-limit violation action	—	✓	✓	✓	✓	✓	✓	—	—

Feature	GUI Supported	112D-POE	FSR-124D	1xxE, 1xxF	4xxE	200 Series, 400 Series	500 Series	1024D, 1024E, 1048D, 1048E, T1024E	3032D, 3032E
set mac-violation-timer	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Sticky MAC	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Warning when the layer-2 table is getting full	—	—	✓	—	✓	✓	✓	—	—
MSTP instances	—	0-15	0-15	0-15	0-15	0-15	0-32	0-32	0-32
STP root guard	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
STP BPDU guard	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Rapid PVST interoperation	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
'forced-untagged' or 'force-tagged' setting on switch interfaces	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Private VLANs	✓	—	✓	—	✓	✓	✓	✓	✓
Multi-stage load balancing	—	—	—	—	—	—	—	✓	✓
Priority-based flow control	—	—	—	—	—	—	✓	✓	✓
Ingress pause metering	—	—	—	—	🔗	🔗	🔗	🔗	🔗 (3032D)
Storm control	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Per-port storm control	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Global burst-size control	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
MAC/IP/protocol-based VLAN assignment	✓	✓	✓	✓	✓	✓	✓	✓	✓
Virtual wire	✓	—	✓	—	✓	✓	✓	✓	✓
Loop guard	✓	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Percentage rate control	🔗	—	🔗	—	🔗	🔗	🔗	🔗	🔗
VLAN stacking (QnQ)	✓	—	✓	—	✓	✓	✓	✓	✓

Feature	GUI Supported	112D-POE	FSR-124D	1xxE, 1xxF	4xxE	200 Series, 400 Series	500 Series	1024D, 1024E, 1048D, 1048E, T1024E	3032D, 3032E
VRF (IPv4/IPv6)	—	—	—	—	—	—	✓	✓	✓
Static BFD (IPv4/IPv6)	✓	✓	✓	✓	✓	✓	✓	✓	✓
BFD for BGPv6	—	—	—	—	—	—	✓	✓	✓
BFD for RIPng	—	—	—	—	✓	✓	✓	✓	✓
uRPF	—	—	—	—	—	—	✓	✓	✓
DHCP relay (IPv4)	✓	—	✓	✓	✓	✓	✓	✓	✓
DHCP server (IPv4)	✓	—	—	—	✓	4xx only	✓	✓	✓
High Availability									
MCLAG (multichassis link aggregation)	Partial	—	—	—	🔗	🔗	🔗	🔗	🔗
STP supported in MCLAGs	—	—	—	—	🔗	🔗	🔗	🔗	🔗
IGMP snooping support in MCLAG	✓	—	—	—	🔗	🔗	🔗	🔗	🔗
Layer-3 (IPv4) routing in MCLAG	—	—	—	—	VRRP and static	VRRP and static	✓	✓	✓
Quality of Service									
802.1p support, including priority queuing trunk and WRED	✓	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗
QoS queue counters	—	—	🔗	—	🔗	🔗	🔗	🔗	🔗
Tail-drop policy	✓	✓	✓	✓	✓	✓	✓	✓	✓
RED drop policy	✓	—	✓	—	—	✓	—	—	—
WRED drop policy	✓	—	—	—	✓	—	✓	✓	✓
Egress drop mode	—	—	—	—	—	—	✓	✓	✓
QoS marking (IPv4/IPv6)	—	—	✓	—	✓	✓	✓	✓	✓
Summary of configured queue mappings	🔗	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗

Feature	GUI Supported	112D-POE	FSR-124D	1xxE, 1xxF	4xxE	200 Series, 400 Series	500 Series	1024D, 1024E, 1048D, 1048E, T1024E	3032D, 3032E
Egress priority tagging (IPv4/IPv6)	—	—	🔗	—	🔗	🔗	🔗	🔗	🔗
ECN (IPv4/IPv6)	✓	—	—	—	🔗	—	🔗	🔗	🔗
Real-time egress queue rates	—	—	—	—	—	✓	✓	✓	✓
Miscellaneous									
PoE-pre-standard detection (See Note 1.)	—	🔗	🔗	🔗 (1xxE-POE)	🔗	🔗	🔗	—	—
PoE modes support: first come, first served or priority based (PoE models)	—	🔗	🔗	🔗 (1xxE-POE)	🔗	🔗	🔗	—	—
Split port (See Note 6.)	Partial	—	—	—	—	—	🔗	🔗 (1048E)	🔗
TDR (time-domain reflectometer)/cable diagnostics support	🔗	—	🔗	🔗	🔗	🔗	🔗	—	—
Auto module max speed detection and notification	✓	—	—	—	—	—	✓	✓	—
Monitor system temperature (threshold configuration and SNMP trap support) (See Note 11.)	—	✓	✓	✓	✓	✓	✓	✓	✓
Cut-through switching	—	—	—	—	—	—	—	1024D, 1048D	✓
Add CLI to show the details of port statistics	—	🔗	🔗	🔗	🔗	🔗	🔗	🔗	🔗
Configuration of the QSFP low-power mode	—	—	—	—	—	—	✓	1024E, 1048D, 1048E, T1024E	✓
Energy-efficient Ethernet	✓	✓	✓	✓	✓	✓	✓	—	—
PHY Forward Error Correction (See Note 5.)	—	—	—	—	—	—	—	1024E, 1048E, T1024E	3032E
PTP transparent clock (IPv4/IPv6) (See Note 9.)	—	—	—	—	🔗	🔗	🔗	🔗 (1024E, 1048E, T1024E)	🔗
Alias commands	—	✓	✓	✓	✓	✓	✓	✓	✓

Notes

1. PoE features are applicable only to the model numbers with a POE or FPOE suffix.
2. The 24-port LAG is applicable to FS-524D, FS-524-FPOE, FS-1024D, and FS-3032D models. The 48-port LAG is applicable to FS-548D, FS-548-FPOE, and FS-1048D models.
3. To use the dynamic layer-3 protocols, you must have an advanced features license.
4. The per-VLAN MAC learning limit is not supported on the FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-124F, FS-124F-POE, FS-124F-FPOE, FS-448D, FS-448D-POE, FS-448D-FPOE, FS-248E-POE, FS-248E-FPOE, and FS-248D models. The per-trunk MAC learning limit is not supported on the FS-448D, FS-448D-POE, FS-448D-FPOE, FS-248E-POE, FS-248E-FPOE, and FS-248D models.
5. Supported only in 100G mode (clause 91).
6. On the FS-3032E, you can split one port at the full base speed, split one port into four sub-ports of 25-Gbps each (100G QSFP only), or split one port into four sub-ports of 10-Gbps each (40G or 100G QSFP).
7. Supported on FS-5xxD 10G ports.
8. The maximum number of access VLANs on the FS-1xxE, FS-108F, FS-108F-POE, and FS-108F-FPOE models is 16; the maximum number of access VLANs on the FS-148F models is 32.
9. PTP is not supported on the FS-248E, FS-248E-POE, FS-248E-FPOE, FS-448D, FS-448D-POE, and FS-448D-FPOE models.
10. In FortiLink mode, static routing is supported exclusively for system management and connectivity to Security Fabric connectors.
11. This feature is not supported by the FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124F, and FS-224E models.

Copyright© 2022 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features, or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.